

Acorn Customer Services

Newsletter

Issue 17
May / June 1993

Editorial

Welcome to Customer Service News Issue 17, This month's newsletter contains some very important information regarding spares pricing and part numbers, Please file this information away with your main Spares Price List,

With this issue of the newsletter we were going to issue the new FCO's in electronic form however it was felt more important to release the new printer manager. We will now issue the new FCO's and all application notes in electronic format on the next CS News Disc.

Peter Dunn
Acorn Computers Ltd

Index

Page Item

2 Acorn News

- CDFS Upgrade
- PocketFS and VProtect
- CSNews Issue 17 Disc Contents
- Replacing your computer's batteries

2 Technical Information

- RISC OS 3 CMOS Problems
- Panasonic KXP2124 incompatibility

3 Technical Information

- Acorn IDE Hard Disc Information

4 Spares / Service Information

- Spares price update
- RISC OS 3 Self Test Information

Additional Inserts

Dealers / ASC Only

A4000 Assembly / Disassembly details
Spares Ordering Terms & Conditions
A3010 Spares Price List A3020 Spares
Price List A4000 Spares Price List
A5000 Spares Price List A4 Spares Price
List (UK Version) /
A4 Spares Price List(Overseas Version)
PocketBook out-of-warranty' service
details
FCO 2022 Update

Every effort has been made to ensure that the information in *this leaflet* is true and correct at the time of printing. However, the products described in this leaflet are subject to continuous development and improvements and Acorn Computers Limited reserves the right to change its specifications at any time. Acorn Computers Limited cannot accept liability for any loss or damage arising from the use of any information or particulars in this leaflet. ACORN, ECONET and ARCHIMEDES are trademarks of Acorn Computers Limited. UNIX is a trademark of AT&T. ETHERNET is a trademark of Xerox Corporation.



Acorn News

CDFS Upgrade

A new SCSI/CDFS upgrade (CDFS 2,13) will be available shortly, This new upgrade allows Acorn SCSI cards (AKA31 and AKA32) to be used with the Acorn Multimedia Expansion unit, The new SCSI/CDFS upgrade should be ordered from your normal supplier, Product Code AKA34,

PocketFS and VProtect

Due to an incompatibility between PocketFS and early versions of VProtect, when you attempt to run !PocketFS the following message is displayed by PocketFS:

'Please quit PocketFS from the Icon Bar'

Pineapple Software have kindly agreed to modify VProtect to avoid the problem and a new version of VProtect can be obtained from them if you are experiencing this problem,

CS News Issue 17 Disc Contents.

This months Customer Service News Issue 17 Disc contains a new version of the !Printers application, The new version (0,34) is intended to improve printing on single floppy drive systems, The are also a number of other advantages to using the software

such as speed of loading, On the disc with the !Printers application and !Scrap are two documentation files which will need to be read and understood to use the new !Printers Application.

Replacing Your Computer's Batteries.

Since 1986 Acorn has used CMOS RAM within its computers to hold various settings about how the machine is set up upon switch on,

The BBC Master 128 uses a set of three batteries shrink wrapped into a complete unit which plugs via a flying lead onto the motherboard (connector PL8), Acorn recommends that the batteries be replaced once every 12 months to ensure that the integrity of the CMOS RAM, The Acorn product code for the BBC Master 128 battery pack is ADT16, Only the Acorn part ADT16 should be used,

The Acorn 300 and 400 Series Archimedes computers were also fitted with batteries; the difference is that the batteries are just two standard AA-size alkaline batteries, *Do not use batteries with non-leakproof cells.* If they leak they may damage the inside of the computer, Again it is recommended the batteries are replaced once a year, Please refer to the User/Welcome guide supplied with the system for further details on dismantling the computer.

Technical Information

RISC OS 3 CMOS Problems

We have received a number of reports of systems not powering up correctly when fitted with a RISC OS 3 upgrade. We suspect this is due to rogue CMOS RAM settings which occurred while the system was used with RISC OS 2,

We strongly recommend that a 'DELETE power on' is performed before the RISC OS 2 upgrade is removed. This will ensure that CMOS RAM locations now used by RISC OS 3 are set correctly,

Panasonic KXP2124 Firmware incompatibility

We have become aware of an incompatibility between versions 'M124E' of the KXP2124 firmware and the RISC OS 3.1 printer manager,

ROMS marked with 'IC3 M124C' and 'IC M124F' ie, versions 'C' and 'F' of the firmware work correctly. The problem with revision 'E' of the firmware is that the printer appears to ignore all data from the parallel port. ie. it fails to print. The printer definition file used on the KXP2124 is Epson LQ860. Panasonic have requested that dealers contact them on their customers behalf for upgrades,

Technical Information

Acorn IDE Hard Disc Information

We are commonly asked for details on the IDE hard discs fitted to various Acorn systems, Below are three diagrams which we believe will provide answers to all your questions regarding the drives we use and have used in the past,

Master					Slave				
Drive	Link Settings				Drive	Link Settings			
	HSP	C/D	DSP	ACT		HSP	C/D	DSP	ACT
CP3044 CP30084E CP30126 CP30174E		✓ ✓ ✓ ✓		✓		No slave drive			
CP3044		✓ ✓ ✓ ✓	✓ ✓ ✓ ✓	✓ ✓ ✓ ✓	CP3044 CP30084E CP30126 CP30174E				✓
CP30084E		✓ ✓			CP3044 CP30126				✓
CP30126		✓ ✓ ✓	✓ ✓ ✓		CP3044 CP30084E CP30174E				✓
CP30174E		✓ ✓			CP3044 CP30126				✓

Model	Size (Mb)	Cyl	Heads	SPT*	BPS2
CP3044	40	526	4	40	512
CP30084E	80	903	4	40	512
CP30126	120	1524	4	39	512
CP30174E	162	762	8	39	512
CP2064	60	823	4	38	512

*Sectors per track
2
Byres per sector

1DE Drive:	Capacity:	Size:	Fitted to:	Firmware Revision:
Conner CP3044	40 Mbytes	3.5" Internal	A5000 Learning Curve A5000 40Mb Hard disc system	2SA4.53
Conner CP30084E	80 Mbytes	3.5" Internal	A4000 Home Office A5000 80Mb Hard disc system	2.39
Conner CP30126	120 Mbytes	3.5" Internal	A5000 120Mb Hard disc system	2.77
Conner CP30174E	162 Mbytes	3.5" Internal	A5000 162Mb Hard disc system	x
Conner CP2064	60 Mbytes	2.5" Internal	A4 A3020 Hard disc system	1.14

Dealer Spares Lists

Please find enclosed spares lists for the A3010, A3020, A4000, A5000 and A4. Your orders should be placed with your usual supplier.

We would like to draw your attention to the following points:-

- a) The prices quoted are dealer prices (excluding VAT) and are subject to change without prior notice.
- b) Supply of spares may be restricted to maximum order levels at time to time, at the discretion of Acorn Computers Ltd.
- c) Every effort has been made to ensure that the information contained in these price lists is true and correct at the time of printing. Acorn Computers Ltd gives no guarantee or warranty concerning the accuracy of the information and shall not be responsible for any loss or damage, of whatever nature, resulting from the use of, or reliance upon, such information.
- d) Acorn Computers Ltd reserves the right to make changes in the products or specifications (or both) presented in these price lists, at any time and without prior notice.

A3010

Dealer Spares List

AGB11, AGB12, AGB15, ALC15

Part Number	Description	Price ,(£)
0194,011	Keyboard	20,96
0194,003	1 Meg Main PCB	228,80
0912,022	Floppy Drive (3,5")	57,50
0999,994	Floppy Drive Shutter (Grey)	0,10
0999,995	Floppy Drive Eject Button (Green)	0,10
0914,001	Mouse (Grey)	19,10
0999,952	Mouse Retaining Clip	0,86
0999,340	Mouse Ball	2,37
0194,015	Mains Cable Assy	5,34
0192,082	Speaker Cable Assy	4,12
0194,075	Disc Drive Pwr Cable Assy	2,60
0194,078	Earth Cable Assy	3,00
2201,102	TV Lead	2,00
0494,042	Name / LED Label	0,90
0494,043	Base Label	0,44
0494,047	Rear Label	2,20
0805,705	Cap PB 5mmD Plastic Grey (reset switch cap)	0,36
0194,077	Screened Case Upper	8,50
0294,065	Plastic Case Lower	8,50
0294,060	Lower Metal	4,02
0294,061	Upper Metal	6,87
0294,062	User Access Lid	4,08
0294,066	Rear Aperture Cover	0,68
0294,070	Rear EMC Blanking Guide	1,76
0296,054	Risc OS Support Disc	5,40
0296,065	Risc OS Apps Disc	5,40
0494,050	Welcome guide	4,25
0496,075	Risc OS User / Apps guide	17,00
0294,095	Outer Carton	9,24
0294,098	Accessories/Manual Carton	4,52
0294,096	Computer LH End Cheek	1,08
0294,097	Computer RH End Cheek	1,08
0393,804	Main PCBa Transit Packing	-
0393,801	3,5" FDD Transit Packing	-

A3020 2MByte Dealer Spares List AGB22, AGB23

Part Number	Description	Price (f£)
0180,011	Keyboard	16.68
0394,908	Main PCBa 2Meg (No 0/S Roms)	266,20
0912,025	Wini Drive 60MB 2, 5" IDE	235,80
0912,024	Floppy Drive 1/2MB 3, 5"	57.50
0999,005	Floppy Drive Shutter (Beige)	0.10
0999,997	Floppy Drive Eject Button (Grey)	0,10
0914,000	Mouse (cream)	19,10
0999,949	Mouse Retaining Clip	0,86
0999,340	Mouse Ball	2,37
0194,015	Mains Cable Assy	5,34
0192,082	Speaker Cable Assy	4,12
0194,078	Earth Cable Assy	3.00
0194,075	Disc Drive Pwr Cable Assy	2,60
0194,565	Hard Drive Cable Assy	12,38
0494,542	Name / LED Label	0,90
0494,543	Base Label	2,20
0494,547	Rear Label	0,72
0805,705	Cap PB 5mmD Plastic Grey	0,36
0294,564	Rear Aperture Cover	0,68
0294,062	User Access Lid	4,08
0294,070	Rear EMC Blanking Gasket	1,76
0294,561	Plastic Case Lower	8,50
0194,563	Screened Case Upper	8,50
0294,560	Lower Metal	4,02
0294,061	Upper Metal	6,87
0296,054	Support Disc	5,40
0296,065	Apps Disc	5,40
0494,550	Welcome Guide	4,25
0496,075	User/Apps Guide	17,00
0294,595	Outer Carton	9,24
0294,096	LH Side Cheek	1.08
0294,097	RH Side Cheek	1,08
0294,098	Accessory / Manual Tray	4,52

<u>Par Number</u>	<u>Description</u>	<u>Price .(£)</u>
0393,804	PCBa Transit Pack (A3020/A0301/A4000)	
0393,806	2,5" Drive Transit Pack	
0393,801	3,5" Drive Transit Pack	

A4000

Dealer Spares List

AGC10, AGC20

Part Number	Description	Price .(£)
0394,910	Main PCBa - 2MByte	235,60
0194,610	PSU	40,00
0391,100	Cased Keyboard	69,00
0912,016	Disc Drive 3, 5 x 1" 2MB	46,38
0912,026	Wini Drive 80MB 3, 5" IDE	212,41
0914,000	Mouse	19,10
0999,949	Retaining Clips	0,86
0999,340	Mouse Ball	2,37
0194,670	Led Cable Assy	3,90
0194,671	Disc Drive Cable Assy	3,80
0194,672	Speaker Cable Assy	3,75
0194,673	Hard Disc Cable Assy	3,80
0870,353	Mains Cable Assy	4,59
0280,073	Rear Blanking Panel	3,63
0292,076	Plastic Push Button	0,28
0294,660	Front Moulding	5,15
0296,054	RISC OS Support Disc	5,40
0296,065	RISC OS Apps Disc	5,40
0494,650	RISC OS Welcome Guide	4,25
0496,075	RISC OS User/Apps Guide	17,00
0294,695	Carton Set	15,20
0393,804	PCBa Transit Pack (A3010/A3020/A4000)	
0393,801	3,5" FDD/HDD Transit Pack	
0393,808	A4000 PSU Transit Pack	

A5000

Dealer Spares List

ALB12, ALB22, ALB24

Part Number	Description	Price .(£)
0192,004	Backplane	26,42
0192,014	PSU	60,84
0912,016	Disc Drive 3, 5x1" 2MB	46,38
0912,023	Wini Drive 120MB 3,5" (ALB24)	258,00
0912,026	Wini Drive 80MB 3, 5" (ALB22)	212,41
0912,017	Wini Drive 40MB 3,5" (ALB12)	202,30
0392,301	2Meg PCB - no 0/S ROMS (ALB12/ALB22)	422,00
0392,303	4Meg PCB - no 0/S ROMS (ALB24)	453,00
0914,000	Mouse	19,10
0999,949	Retaining Clips	0,86
0999,340	Mouse Ball	2,37
0392,900	Cased Keyboard	79,50
0192,900	Keyboard PCBa	30,08
0186,012	Keyboard Assy (keytops)	19,22
0192,910	Curly Keyboard Cable	13,24
0805,704	Reset Switch	0,68
0276,108	Reset Switch Cap	1,08
0276,103	Leg Moulding	0,75
0286,920	K/B Case Lower	7,20
0286,921	K/B Case Upper	7,20
0192,080	Led Cable Assy	4,36
0192,081	Disc Drive Cable Assy	4,16
0192,082	Speaker Cable Assy	4,12
0192,180	Hard Disc Cable Assy	4,20
0870,353	Mains Lead	4,59
0270,256	Risc OS 3,0 Apps Disc 1 (ALB 12)	5,40
0270,258	Risc OS 3,0 Apps Disc 2 (ALB12)	5,40
0270,260	Risc OS 3,0 Support Disc (ALB12)	5,40
0470,281	Risc OS 3.0 User Guide (ALB12)	10,52
0470,282	Risc OS 3,0 Apps Guide (ALB12)	9,68
0492,050	Risc OS 3.0 Welcome Guide (ALB12)	3,24
0296,065	Risc OS 3,1 Apps Disc (ALB22/ALB24)	5,40
0296,054	Risc OS 3.1 Support Disc (ALB22/ALB24)	5,40
0496,071	Risc OS 3,1 User Guide (ALB22/ALB24)	TBA
0496,072	Risc OS 3,1 Apps Guide(ALB22/ALB24)	TBA
0492,250	Risc OS 3.1 Welcome Guide	TBA

<u>Part Number</u>	<u>Description</u>	<u>Price .W</u>
0292,070	Front Moulding	3,72
0292.074	Floppy Aperture Cover	1,40
0292,075	Blanking Panel -Floppy	0,24
0292,076	Plastic Push Button	0,28
0492,041	Front Label	1,44
0292.084	Outer Carton	5,11
0292,085	Computer Carton	2,64
0292,086	Keyboard Carton	3,08
0292,087	Accessories/Manual Carton	3,08
0292,088	Pizza Tray Spacer	3,08
0292,089	Pizza Tray Filler	2,35
0393,800	A5000 PCB Transit Pack	
0393,803	A5000 PSU Transit Pack	
0393.801	3.5" Disc Drive Transit Pack	

A4

Dealer Spares List

AKB62, AKB64

Part Number	Description	List Price .(,£)
0914,001	Mouse (Grey) 200DPI	19,10
0999,340	Mouse Ball	2,37
0999,952	Mouse Retaining Clip	0.86
0870,353	Mains Cable Assy	4,59
0190,120	Side Drop Flap	1,70
0190,125	Rear Drop Flap	3,24
0490,050	Welcome Guide	7,80
0490,051	Portable Guide	5,85
0496,075	Risc OS 3 User / Apps Guide	17.00
0296,065	RISC OS 3 Apps Suite Disc	5.40
0296,054	Support Disc	5,40

Out of warranty PocketBook Repair Price List

All the prices listed below are out of warranty repair prices for Psion related products issued by Psion in January 1993,

	Price ex. VAT	Price inc. VAT	Delivery Business Post
PocketBook 128K and 256K			
Any fault incl, broken screen	£45,00	£52,87	£5,88
Cosmetic Upgrade (made as new, exclusiye of packaging)	£25,00	£29,37	£5,88
-128K upgraded to 256K	£76,66	£89,95	£5,88
Solid State Disks(SSDs)			
128K Flash SSD	£17,00	£19,98	£5,88
256K Flash SSD	£23,00	£27,03	£5,88
512K Flash SSD	£30,00	£35,25	£5,88
1 Mbyte	£42,00	£49,35	£5,88
2 Mbyte	£70,00	£82,25	£5,88
128K Ram SSD	£21,00	£24,68	£5,88
512K Ram SSD	£42,00	£49,35	£5,88
1 Mbyte Ram SSD	£70,00	£82,25	£5,88
PROGRAM PACKS			
All Types	£20,00	£23,50	£5,88
PERIPHERALS			
Parallel Link	£15,00	£17,62	£5,88

Note: Mains Adapters and Link-up Adapters cannot be repaired

Psion reserves the right to echange prices, product ranges and technical specification without prior notice.

Psion Repair Centre 17 - 19 Bristol Road, Greenford, Bristol, Middlesex, UB6 8UP
Telephone 081 575 9919